



# OWR-3083T-150WB

## Wide band receiver

Optimized for P.311 or TIA820A and also HAC compatible



## Characteristics

<b>Size (ØxH) [mm]</b>	30.0x8.5	
<b>Sensitivity [dBSPL]</b>	100.0±3dB	[dBSPL @1kHz, 1mW, 2cc]
<b>Impedance [Ω]</b>	150	
<b>Power [W]</b>	10.0 / 30.0	Free field
<b>F0 [Hz]</b>	160	Free field
<b>Termination</b>	Terminals	

Specifications are subject to change without prior notice. Upon request Ole Wolff can supply further specifications, simulation parameters etc.

## Mecanical drawing

