

OWR-1203T-32A

ANC Driver

Optimized for ANC applications, excellent performance.



Characteristics

| | | |
|----------------------------|-------------|-------------------------|
| Size (ØxH) [mm] | 12.0x3.0 | |
| Sensitivity [dBSPL] | 81.0±3dB | [dBSPL@179 mV,ff, 1kHz] |
| Impedance [Ω] | 30 | |
| Power [W] | 10.0 / 20.0 | Free field |
| F0 [Hz] | 250 | Free field |
| Termination | Terminals | |

Specifications are subject to change without prior notice. Upon request Ole Wolff can supply further specifications, simulation parameters etc.

Mecanical drawing

